


## XPP-5418GX • XPP-5418RX

### X-Series Intrinsically Safe Flashlight

<b>MARKET APPLICATIONS</b>	Hazardous work environments, industrial, automotive, fire and rescue
<b>DESCRIPTION</b>	This Flashlight is cETLus, ATEX, and IECEx listed Intrinsically Safe for use in both above and below ground hazardous locations where explosive gases and dusts may be present. The XPP-5418GX/RX uses a CREE® LED rated at 200 lumens that works in conjunction with a high-efficiency deep parabolic reflector to create a usable flashlight beam rated at 143 meters. The tail switch provides momentary or constant-on functionality. Meets the requirements of NFPA-1971-8.6 (2013). Power comes from 3 AA premium batteries (not included).
<b>CASE MATERIAL</b>	Glass-Filled Nylon Polymer
<b>DIMENSIONS</b>	Length 5.6 in. • Head Diameter 1.5 in. • Handle Diameter .75 x 1.4 in.
<b>WEIGHT</b>	5.4 oz.
<b>LIGHT SOURCE</b>	CREE® LED technology – 50,000 + hours LED life
<b>LIGHT OUTPUT</b>	Flashlight Lumens: 200
<b>ON/OFF</b>	Tailswitch. Momentary and constant on/off
<b>RUN-TIME</b>	10.5 hrs.
<b>BATTERY</b>	3 AA Batteries (not included)
<b>FEATURES</b>	<ul style="list-style-type: none"> <li>• cETLus, ATEX, and IECEx listed Intrinsically Safe for use in both above and below ground hazardous locations where explosive gases and dusts may be present</li> <li>• Sharp focused flashlight beam for distance illumination</li> <li>• Non-slip grip</li> <li>• Dustproof / Waterproof</li> <li>• Impact and chemical resistant</li> <li>• Meets Requirements of NFPA-1971-8.6 (2013)</li> </ul>
<b>WARRANTY</b>	Limited Lifetime Warranty

**APPROVALS**



 Intertek E 467756 INTRINSICALLY SAFE SECURITE INTRINSEQUE CE 0359	<b>Bayco Products, Inc. XPP-5418GX/RX</b> 640 S. Sanden Blvd., Wylie, TX 75098 Ex ia FLASHLIGHT FOR USE IN HAZARDOUS LOCATIONS CLASS I DIV 1 GRPS A-D T3 CLASS II & III DIV 1 GRPS E-G T135°C CLASS I ZONE 0 AEx ia IIC T3 Ga Ex ia IIC T3 Ga Ⓢ II 1 G Ex ia op is IIC T3 Ga	Ex ia op is IIC T3 Ga Intertek ITS 13 ATEX27837X IECEx ITS 16.0067X -20°C ≤ Tamb ≤ +40°C 1.5V/Cell with three in series Energizer E91 or EN91
<b>WARNINGS:</b> Replace batteries in a non-hazardous location. Use only Energizer AA Model E91 or EN91 batteries. <b>AVERTISSEMENT:</b> Remplacer les piles dans une zone non dangereuse. Utiliser uniquement les piles Energizer AA - modèle E91 ou EN91.		

